

Light-O-Rama



LOR800D-MP3

ShowTime
Show-in-a-Box
Light Controller + MP3 Director

www.lightorama.com

- Plays MP3s while directing itself and a network of controllers
- Eliminates the need for a Windows PC to run the show
- SD card stores shows and music
- SD card show can run continuously or in response to switch closures
- Metal power strip style box
- Compact for unobtrusive use indoors
- 8 independent high-power channels
- 15 amp capacity (about 4500 mini-lights)
- Effects include on, off, fade, intensity, twinkle and shimmer
- Up to 240 controllers in a network
- 100 intensity levels for dimming
- 256 levels for smooth fading with durations from 0.1 to 25 seconds
- Settable high burn (to extend lamp life) and low burn (to reduce lamp shock)
- Can power a wireless unit for additional installation flexibility

Complete Musical Light Show in a Box



Light-O-Rama's easy to use ShowTime Windows Software with its powerful wizards lets you create beautiful light shows and animations that can even be choreographed to music.

Load your completed shows on to an SD memory card and plug the card into an LOR Show-in-a-Box controller, turn it on and you have a completely self-contained show. You get stereo line outputs for the MP3 audio, 8 high-power channels for lighting control and network connections to drive additional controllers and/or an RF-V4 Wireless Module.

Switch closures can trigger a show making the animation of startling Halloween displays especially easy.

One microprocessor runs your show and plays the music, a second microprocessor handles sophisticated lighting effects.

A network of controllers allows animation of displays requiring high power and/or thousands of channels.



Specifications

Specifications	
Channel Capacity	8 amps
Controller Capacity	15 amps
Supply Voltage	120 VAC 50/60 Hz
Control In/Out	RS485 via RJ45 or RJ11
Dimensions (case)	9"w x 4"h x 2"d

Light-O-Rama, Inc.

Tel: (518) 539-9000 Fax (518) 538-0067
info@lightorama.com